


The RF Line **NPN Silicon** **Low Noise, High-Frequency** **Transistors**

Designed for use in high gain, low noise small-signal amplifiers. This series features excellent broadband linearity and is offered in a variety of packages.


- Fully Implanted Base and Emitter Structure
- 9 Finger, 1.25 Micron Geometry with Gold Top Metal
- Gold Sintered Back Metal
- Available in tape and reel packaging options:
 - T1 suffix = 3,000 units per reel
 - T3 suffix = 10,000 units per reel

MMBR941 **MRF947** **MRF9411** **SERIES**


$I_C = 50 \text{ mA}$
LOW NOISE
HIGH-FREQUENCY
TRANSISTORS



CASE 318-08, STYLE 6
SOT-23
LOW PROFILE
MMBR941LT1, T3, MMBR941BLT1



CASE 419-02, STYLE 3
MRF947AT1, MRF947BT1,
MRF947T1, T3



CASE 318A-05, STYLE 1
SOT-143
LOW PROFILE
MRF9411LT1



MAXIMUM RATINGS

| Rating | Symbol | MMBR941LT1, T3 | MRF9411LT1 | MRF947 Series | Unit |
|---|-----------------|----------------|--------------|---------------|-------------------------------|
| Collector–Emitter Voltage | V_{CEO} | 10 | 10 | 10 | Vdc |
| Collector–Base Voltage | V_{CBO} | 20 | 20 | 20 | Vdc |
| Emitter–Base Voltage | V_{EBO} | 1.5 | 1.5 | 1.5 | Vdc |
| Power Dissipation (1) $T_C = 75^\circ\text{C}$ Derate linearly above $T_{case} = 75^\circ\text{C}$ @ | P_{Dmax} | 0.25 3.33 | 0.25 3.33 | 0.188 2.5 | Watts mW/ $^\circ\text{C}$ |
| Collector Current — Continuous (2) | I_C | 50 | 50 | 50 | mA |
| Maximum Junction Temperature | T_{Jmax} | 150 | 150 | 150 | $^\circ\text{C}$ |
| Storage Temperature | T_{stg} | –55 to +150 | –55 to +150 | –55 to +150 | $^\circ\text{C}$ |
| Thermal Resistance, Junction to Case | $R_{\theta JC}$ | 300 | 300 | 400 | $^\circ\text{C/W}$ |

DEVICE MARKING

| | | | |
|------------------------------------|-----------------------------------|------------------|---------------|
| MMBR941LT1 = 7Y MRF9411LT1 = 10 | MMBR941BLT1 = 7N MRF947AT1 = G | MRF947T1, T3 = A | MRF947BT1 = H |
|------------------------------------|-----------------------------------|------------------|---------------|

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted)

| Characteristic | Symbol | Min | Typ | Max | Unit |
|----------------|--------|-----|-----|-----|------|
|----------------|--------|-----|-----|-----|------|

OFF CHARACTERISTICS (3)

| | | | | | | |
|--|-----|---------------|----|----|-----|-----------------|
| Collector–Emitter Breakdown Voltage ($I_C = 0.1\text{ mA}$, $I_B = 0$) | All | $V_{(BR)CEO}$ | 10 | 12 | — | Vdc |
| Collector–Base Breakdown Voltage ($I_C = 0.1\text{ mA}$, $I_E = 0$) | All | $V_{(BR)CBO}$ | 20 | 23 | — | Vdc |
| Emitter Cutoff Current ($V_{EB} = 1.0\text{ V}$, $I_C = 0$) | All | I_{EBO} | — | — | 0.1 | μAdc |
| Collector Cutoff Current ($V_{CB} = 10\text{ V}$, $I_E = 0$) | All | I_{CBO} | — | — | 0.1 | μAdc |

ON CHARACTERISTICS (3)

| | | | | | |
|--|-------------------------------------|-----------------|-------------|-----------------|---|
| DC Current Gain ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$) (MMBR941LT1, MRF9411LT1) (MMBR941BLT1) | h_{FE} | 50 100 | — — | 200 200 | — |
| DC Current Gain ($V_{CE} = 1.0\text{ V}$, $I_C = 500\text{ }\mu\text{A}$) MRF947T1, MRF947BT1 | h_{FE1} | 50 | — | — | — |
| DC Current Gain ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$) MRF947T1, T3 MRF947AT1 MRF947BT1 | h_{FE2} h_{FE3} h_{FE4} | 50 75 100 | — — — | — 150 200 | — |

DYNAMIC CHARACTERISTICS

| | | | | | | |
|---|-----|----------|---|------|---|-----|
| Collector–Base Capacitance ($V_{CB} = 10\text{ V}$, $I_E = 0$, $f = 1.0\text{ MHz}$) | All | C_{cb} | — | 0.35 | — | pF |
| Current Gain — Bandwidth Product ($V_{CE} = 6.0\text{ V}$, $I_C = 15\text{ mA}$, $f = 1.0\text{ GHz}$) | All | f_T | — | 8.0 | — | GHz |

NOTE:

1. To calculate the junction temperature use $T_J = P_D \times R_{\theta JC} + T_{CASE}$. Case temperature measured on collector lead immediately adjacent to body of package.
2. I_C — Continuous (MTBF ≈ 10 years).
3. Pulse width $\leq 300\text{ }\mu\text{s}$, duty cycle $\leq 2\%$ pulsed.

PERFORMANCE CHARACTERISTICS

| Conditions | Symbol | MRF9411LT1 | | | MMBR941LT1, T3 | | | MRF947 Series | | | Unit |
|--|--------------------|------------|------------|-----|----------------|------------|-----|---------------|--------------|-----|------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| Insertion Gain ($V_{CE} = 6.0\text{ V}$, $I_C = 15\text{ mA}$, $f = 1.0\text{ GHz}$) ($V_{CE} = 6.0\text{ V}$, $I_C = 15\text{ mA}$, $f = 2.0\text{ GHz}$) | $ S_{21} ^2$ | — | 16 10 | — | — | 14 8.0 | — | — | 14 10.8 | — | dB |
| Maximum Unilateral Gain (1) ($V_{CE} = 6.0\text{ V}$, $I_C = 15\text{ mA}$, $f = 1.0\text{ GHz}$) ($V_{CE} = 6.0\text{ V}$, $I_C = 15\text{ mA}$, $f = 2.0\text{ GHz}$) | $G_{U\text{ max}}$ | — | 18 12 | — | — | 16 10 | — | — | 14.8 11.6 | — | dB |
| Noise Figure — Minimum (Figure 9) ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$, $f = 1.0\text{ GHz}$) ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$, $f = 2.0\text{ GHz}$) | NF _{MIN} | — | 1.5 2.1 | — | — | 1.5 2.1 | — | — | 1.5 2.1 | — | dB |
| Associated Gain at Minimum NF (Figure 9) ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$, $f = 1.0\text{ GHz}$) ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$, $f = 2.0\text{ GHz}$) | G_{NF} | — | 15 9.5 | — | — | 14 8.5 | — | — | 14 10 | — | dB |
| Noise Figure — 50 ohm Source ($V_{CE} = 6.0\text{ V}$, $I_C = 5.0\text{ mA}$, $f = 1.0\text{ GHz}$) | NF _{50 Ω} | — | 1.9 | 2.8 | — | 1.9 | 2.8 | — | 1.9 | 2.8 | dB |

NOTE:

$$1. \text{ Maximum Unilateral Gain is } G_{U\text{ max}} = \frac{|S_{21}|^2}{(1 - |S_{11}|^2)(1 - |S_{22}|^2)}$$

TYPICAL CHARACTERISTICS

MMBR941LT1, T3; MMBR941BLT1; MRF9411LT1; MRF9411BLT1




Figure 1. Collector-Base Capacitance versus Voltage




Figure 2. DC Current Gain versus Collector Current




Figure 3. Gain Bandwidth Product versus Collector Current




Figure 4. Insertion Gain versus Collector Current

FORWARD INSERTION GAIN AND MAXIMUM UNILATERAL GAIN versus FREQUENCY




Figure 5. MMBR941LT1, T3




Figure 6. MRF9411LT1




Figure 7. Noise Figure and Associated Gain
versus Frequency




Figure 8. Minimum Noise Figure versus
Collector Current




Figure 9. Functional Circuit Schematic (all devices)

TYPICAL CHARACTERISTICS MRF947 SERIES




Figure 10. Capacitance versus Voltage




Figure 11. DC Current Gain versus Collector Current




Figure 12. Gain-Bandwidth Product versus Collector Current




Figure 13. Associated Gain and Minimum Noise Figure versus Collector Current




Figure 14. Forward Insertion Gain and Maximum Stable/Available Power Gain versus Frequency

| V _{CE} (Volts) | I _C (mA) | f (MHz) | S ₁₁ | | S ₂₁ | | S ₁₂ | | S ₂₂ | |
|----------------------------|------------------------|------------|-----------------|------|-----------------|-----|-----------------|-----|-----------------|------|
| | | | Mag | ∠ φ | Mag | ∠ φ | Mag | ∠ φ | Mag | ∠ φ |
| 1.0 | 0.5 | 100 | 0.97 | −11 | 1.78 | 170 | 0.03 | 83 | 0.99 | −4.7 |
| | | 200 | 0.96 | −22 | 1.74 | 161 | 0.06 | 76 | 0.99 | −9.1 |
| | | 500 | 0.90 | −53 | 1.60 | 133 | 0.13 | 56 | 0.93 | −21 |
| | | 900 | 0.75 | −89 | 1.37 | 105 | 0.18 | 37 | 0.83 | −33 |
| | | 1000 | 0.72 | −98 | 1.32 | 100 | 0.18 | 33 | 0.82 | −36 |
| | | 1500 | 0.63 | −132 | 1.07 | 74 | 0.19 | 20 | 0.75 | −47 |
| | | 2000 | 0.57 | −163 | 0.89 | 55 | 0.16 | 15 | 0.72 | −57 |
| | | 3000 | 0.55 | 144 | 0.67 | 30 | 0.15 | 40 | 0.71 | −76 |
| | 1.0 | 100 | 0.95 | −13 | 3.37 | 169 | 0.03 | 81 | 0.99 | −6.2 |
| | | 200 | 0.93 | −27 | 3.27 | 158 | 0.06 | 73 | 0.98 | −12 |
| | | 500 | 0.81 | −62 | 2.85 | 128 | 0.12 | 52 | 0.86 | −26 |
| | | 900 | 0.63 | −101 | 2.21 | 101 | 0.15 | 37 | 0.73 | −38 |
| | | 1000 | 0.60 | −110 | 2.08 | 96 | 0.15 | 34 | 0.71 | −40 |
| | | 1500 | 0.51 | −144 | 1.59 | 73 | 0.16 | 27 | 0.64 | −49 |
| | | 2000 | 0.46 | −173 | 1.28 | 56 | 0.16 | 29 | 0.61 | −58 |
| | | 3000 | 0.46 | 138 | 0.95 | 30 | 0.19 | 44 | 0.60 | −75 |
| 6.0 | 5.0 | 100 | 0.82 | −25 | 14.6 | 159 | 0.02 | 77 | 0.94 | −13 |
| | | 200 | 0.75 | −47 | 12.6 | 142 | 0.04 | 68 | 0.85 | −22 |
| | | 400 | 0.55 | −79 | 9.2 | 120 | 0.05 | 61 | 0.69 | −31 |
| | | 600 | 0.42 | −98 | 6.9 | 106 | 0.07 | 60 | 0.60 | −32 |
| | | 800 | 0.33 | −114 | 5.3 | 97 | 0.08 | 61 | 0.56 | −33 |
| | | 1000 | 0.28 | −129 | 4.5 | 90 | 0.09 | 62 | 0.52 | −33 |
| | | 1500 | 0.25 | −155 | 3.1 | 77 | 0.13 | 67 | 0.51 | −37 |
| | | 2000 | 0.16 | 176 | 2.4 | 66 | 0.16 | 68 | 0.51 | −36 |
| | | 2500 | 0.21 | 151 | 2.0 | 57 | 0.20 | 69 | 0.48 | −40 |
| | | 3000 | 0.18 | 122 | 1.7 | 50 | 0.23 | 68 | 0.48 | −44 |
| | | 3500 | 0.30 | 108 | 1.5 | 42 | 0.27 | 66 | 0.45 | −46 |
| | | 4000 | 0.29 | 91 | 1.4 | 37 | 0.32 | 64 | 0.42 | −53 |
| | 10 | 100 | 0.67 | −37 | 23.5 | 149 | 0.02 | 74 | 0.88 | −18 |
| | | 200 | 0.54 | −64 | 18.1 | 129 | 0.03 | 68 | 0.73 | −28 |
| | | 400 | 0.37 | −96 | 11.3 | 108 | 0.05 | 67 | 0.56 | −31 |
| | | 600 | 0.26 | −114 | 8.0 | 98 | 0.06 | 67 | 0.50 | −30 |
| | | 800 | 0.21 | −130 | 6.0 | 91 | 0.08 | 70 | 0.47 | −30 |
| | | 1000 | 0.18 | −147 | 5.1 | 85 | 0.09 | 70 | 0.45 | −30 |
| | | 1500 | 0.18 | −167 | 3.4 | 74 | 0.13 | 72 | 0.46 | −34 |
| | | 2000 | 0.11 | 159 | 2.6 | 64 | 0.17 | 71 | 0.46 | −34 |
| | | 2500 | 0.17 | 140 | 2.2 | 56 | 0.21 | 69 | 0.44 | −38 |
| | | 3000 | 0.15 | 107 | 1.8 | 59 | 0.25 | 67 | 0.45 | −41 |
| | | 3500 | 0.27 | 100 | 1.7 | 42 | 0.28 | 65 | 0.42 | −42 |
| | | 4000 | 0.26 | 85 | 1.5 | 37 | 0.33 | 61 | 0.39 | −49 |
| | 15 | 100 | 0.56 | −46 | 28.6 | 143 | 0.02 | 73 | 0.83 | −22 |
| | | 200 | 0.43 | −75 | 20.2 | 122 | 0.03 | 67 | 0.65 | −30 |
| | | 400 | 0.29 | −107 | 11.8 | 104 | 0.04 | 70 | 0.50 | −30 |
| | | 600 | 0.22 | −125 | 8.2 | 95 | 0.06 | 74 | 0.46 | −28 |
| | | 800 | 0.18 | −141 | 6.2 | 88 | 0.08 | 74 | 0.45 | −27 |
| | | 1000 | 0.16 | −158 | 5.1 | 83 | 0.09 | 74 | 0.43 | −28 |
| | | 1500 | 0.17 | −174 | 3.4 | 72 | 0.13 | 73 | 0.44 | −32 |
| | | 2000 | 0.11 | 150 | 2.6 | 63 | 0.17 | 72 | 0.45 | −33 |
| | | 2500 | 0.17 | 138 | 2.2 | 55 | 0.21 | 70 | 0.43 | −37 |
| | | 3000 | 0.15 | 102 | 1.9 | 49 | 0.25 | 67 | 0.44 | −39 |
| | | 3500 | 0.28 | 98 | 1.7 | 42 | 0.29 | 65 | 0.40 | −41 |
| | | 4000 | 0.25 | 82 | 1.5 | 37 | 0.32 | 61 | 0.38 | −47 |

Table 1. MMBR941LT1, T3 Common Emitter S-Parameters

| VCE (Volts) | IC (mA) | f (MHz) | S11 | | S21 | | S12 | | S22 | |
|----------------|------------|------------|------|---------------|------|---------------|------|---------------|------|---------------|
| | | | Mag | $\angle \phi$ | Mag | $\angle \phi$ | Mag | $\angle \phi$ | Mag | $\angle \phi$ |
| 6.0 | 20 | 100 | 0.49 | -52 | 31.5 | 139 | 0.01 | 70 | 0.79 | -23 |
| | | 200 | 0.36 | -84 | 21.1 | 118 | 0.02 | 69 | 0.60 | -29 |
| | | 400 | 0.25 | -115 | 12.1 | 101 | 0.04 | 73 | 0.48 | -29 |
| | | 600 | 0.20 | -134 | 8.3 | 93 | 0.06 | 74 | 0.45 | -26 |
| | | 800 | 0.16 | -150 | 6.2 | 87 | 0.07 | 75 | 0.44 | -26 |
| | | 1000 | 0.15 | -166 | 5.1 | 82 | 0.09 | 75 | 0.42 | -26 |
| | | 1500 | 0.16 | -176 | 3.5 | 75 | 0.14 | 74 | 0.44 | -31 |
| | | 2000 | 0.12 | 144 | 2.6 | 63 | 0.17 | 73 | 0.45 | -32 |
| | | 2500 | 0.17 | 133 | 2.2 | 55 | 0.22 | 70 | 0.43 | -36 |
| | | 3000 | 0.16 | 101 | 1.9 | 49 | 0.25 | 68 | 0.44 | -39 |
| | | 3500 | 0.28 | 98 | 1.6 | 41 | 0.29 | 65 | 0.41 | -40 |
| | | 4000 | 0.26 | 82 | 1.5 | 36 | 0.33 | 61 | 0.39 | -47 |
| | 30 | 100 | 0.41 | -65 | 34.3 | 134 | 0.01 | 70 | 0.74 | -25 |
| | | 200 | 0.30 | -99 | 21.6 | 113 | 0.02 | 70 | 0.56 | -28 |
| | | 400 | 0.23 | -131 | 11.9 | 98 | 0.04 | 76 | 0.47 | -25 |
| | | 600 | 0.20 | -147 | 8.1 | 91 | 0.06 | 76 | 0.45 | -24 |
| | | 800 | 0.18 | -163 | 6.1 | 84 | 0.07 | 78 | 0.44 | -23 |
| | | 1000 | 0.17 | -177 | 5.0 | 80 | 0.09 | 78 | 0.43 | -24 |
| | | 1500 | 0.18 | 174 | 3.4 | 70 | 0.13 | 76 | 0.45 | -30 |
| | | 2000 | 0.14 | 141 | 2.5 | 61 | 0.17 | 74 | 0.47 | -31 |
| | | 2500 | 0.20 | 131 | 2.1 | 54 | 0.21 | 71 | 0.45 | -36 |
| | | 3000 | 0.18 | 104 | 1.8 | 47 | 0.25 | 69 | 0.46 | -39 |
| | | 3500 | 0.31 | 100 | 1.6 | 40 | 0.29 | 65 | 0.42 | -42 |
| | | 4000 | 0.29 | 84 | 1.5 | 35 | 0.33 | 62 | 0.40 | -48 |

Table 1. MMBR941LT1, T3 Common Emitter S-Parameters (continued)

| VCE (Volts) | IC (mA) | f (MHz) | S11 | | S21 | | S12 | | S22 | |
|----------------|------------|------------|------|---------------|------|---------------|------|---------------|------|---------------|
| | | | Mag | $\angle \phi$ | Mag | $\angle \phi$ | Mag | $\angle \phi$ | Mag | $\angle \phi$ |
| 1.0 | 0.5 | 100 | 0.97 | -10 | 1.78 | 171 | 0.03 | 83 | 100 | -4.7 |
| | | 200 | 0.97 | -20 | 1.75 | 163 | 0.05 | 77 | 100 | -9.2 |
| | | 500 | 0.93 | -49 | 1.62 | 137 | 0.12 | 57 | 0.94 | -21 |
| | | 900 | 0.81 | -84 | 1.43 | 110 | 0.18 | 36 | 0.86 | -35 |
| | | 1000 | 0.79 | -92 | 1.38 | 104 | 0.19 | 32 | 0.84 | -38 |
| | | 1500 | 0.72 | -125 | 1.12 | 78 | 0.20 | 14 | 0.77 | -50 |
| | | 2000 | 0.68 | -152 | 0.92 | 57 | 0.20 | 1 | 0.74 | -61 |
| | | 3000 | 0.66 | 169 | 0.68 | 27 | 0.16 | -11 | 0.73 | -82 |
| | 1.0 | 100 | 0.95 | -13 | 3.37 | 170 | 0.03 | 82 | 0.99 | -6.2 |
| | | 200 | 0.94 | -25 | 3.30 | 161 | 0.05 | 74 | 0.98 | -12 |
| | | 500 | 0.88 | -59 | 2.96 | 133 | 0.16 | 53 | 0.89 | -27 |
| | | 1000 | 0.70 | -107 | 2.26 | 101 | 0.16 | 29 | 0.74 | -44 |
| | | 1500 | 0.64 | -139 | 1.72 | 78 | 0.17 | 15 | 0.66 | -55 |
| | | 2000 | 0.61 | -165 | 1.36 | 59 | 0.17 | 6.7 | 0.62 | -65 |
| | | 3000 | 0.61 | 160 | 0.97 | 32 | 0.14 | 3.0 | 0.61 | -84 |

Table 2. MRF9411LT1 Common Emitter S-Parameters

| V _{CE} (Volts) | I _C (mA) | f (MHz) | S ₁₁ | | S ₂₁ | | S ₁₂ | | S ₂₂ | |
|----------------------------|------------------------|------------|-----------------|------|-----------------|-----|-----------------|-----|-----------------|------|
| | | | Mag | ∠ φ | Mag | ∠ φ | Mag | ∠ φ | Mag | ∠ φ |
| 6.0 | 5.0 | 100 | 0.73 | −24 | 14 | 164 | 0.02 | 92 | 0.96 | −11 |
| | | 200 | 0.74 | −47 | 12.9 | 150 | 0.03 | 65 | 0.90 | −20 |
| | | 400 | 0.66 | −83 | 10.4 | 129 | 0.05 | 56 | 0.75 | −32 |
| | | 600 | 0.62 | −108 | 8.4 | 115 | 0.06 | 45 | 0.65 | −40 |
| | | 800 | 0.56 | −127 | 6.7 | 105 | 0.07 | 46 | 0.60 | −43 |
| | | 1000 | 0.54 | −141 | 5.6 | 96 | 0.07 | 51 | 0.57 | −46 |
| | | 1500 | 0.46 | −166 | 3.9 | 82 | 0.08 | 55 | 0.52 | −50 |
| | | 2000 | 0.43 | 172 | 2.9 | 70 | 0.09 | 56 | 0.50 | −54 |
| | | 2500 | 0.41 | 151 | 2.3 | 62 | 0.11 | 61 | 0.48 | −60 |
| | | 3000 | 0.44 | 128 | 1.9 | 55 | 0.14 | 62 | 0.49 | −65 |
| | | 3500 | 0.49 | 117 | 1.6 | 47 | 0.15 | 61 | 0.46 | −74 |
| | | 4000 | 0.57 | 101 | 1.4 | 42 | 0.16 | 62 | 0.47 | −81 |
| | | 5000 | 0.60 | 92 | 1.2 | 32 | 0.21 | 60 | 0.46 | −105 |
| | | 6000 | 0.58 | 88 | 1.0 | 20 | 0.25 | 61 | 0.51 | −137 |
| | 10 | 100 | 0.64 | −39 | 23.6 | 157 | 0.01 | 59 | 0.91 | −16 |
| | | 200 | 0.60 | −71 | 20 | 139 | 0.02 | 70 | 0.80 | −27 |
| | | 400 | 0.54 | −112 | 13.9 | 117 | 0.03 | 57 | 0.61 | −39 |
| | | 600 | 0.52 | −135 | 10.3 | 104 | 0.04 | 50 | 0.51 | −43 |
| | | 800 | 0.49 | −151 | 8.0 | 96 | 0.05 | 54 | 0.46 | −44 |
| | | 1000 | 0.47 | −161 | 6.5 | 89 | 0.06 | 60 | 0.46 | −46 |
| | | 1500 | 0.41 | 177 | 4.4 | 77 | 0.08 | 62 | 0.44 | −47 |
| | | 2000 | 0.40 | 158 | 3.2 | 67 | 0.09 | 65 | 0.43 | −52 |
| | | 2500 | 0.39 | 139 | 2.6 | 60 | 0.11 | 68 | 0.41 | −56 |
| | | 3000 | 0.44 | 118 | 2.1 | 53 | 0.13 | 69 | 0.43 | −62 |
| | | 3500 | 0.49 | 110 | 1.8 | 47 | 0.15 | 67 | 0.39 | −72 |
| | | 4000 | 0.54 | 96 | 1.6 | 42 | 0.18 | 65 | 0.41 | −78 |
| | | 5000 | 0.63 | 88 | 1.3 | 32 | 0.23 | 61 | 0.40 | −101 |
| | | 6000 | 0.58 | 86 | 1.1 | 20 | 0.26 | 62 | 0.44 | −136 |
| | 15 | 100 | 0.56 | −51 | 29.5 | 152 | 0.01 | 78 | 0.87 | −20 |
| | | 200 | 0.53 | −88 | 23.5 | 131 | 0.02 | 63 | 0.73 | −31 |
| | | 400 | 0.51 | −128 | 15.1 | 111 | 0.03 | 63 | 0.54 | −40 |
| | | 600 | 0.49 | −148 | 11.8 | 99 | 0.04 | 56 | 0.46 | −42 |
| | | 800 | 0.48 | −161 | 8.3 | 92 | 0.04 | 59 | 0.42 | −41 |
| | | 1000 | 0.46 | −170 | 6.7 | 86 | 0.05 | 59 | 0.41 | −44 |
| | | 1500 | 0.41 | −171 | 4.4 | 75 | 0.07 | 70 | 0.42 | −45 |
| | | 2000 | 0.40 | 152 | 3.3 | 66 | 0.09 | 71 | 0.41 | −50 |
| | | 2500 | 0.39 | 135 | 2.6 | 59 | 0.11 | 71 | 0.41 | −55 |
| | | 3000 | 0.45 | 116 | 2.2 | 53 | 0.14 | 73 | 0.42 | −61 |
| | | 3500 | 0.50 | 108 | 1.9 | 46 | 0.17 | 70 | 0.39 | −70 |
| | | 4000 | 0.55 | 94 | 1.6 | 41 | 0.19 | 67 | 0.41 | −76 |
| | | 5000 | 0.61 | 87 | 1.3 | 32 | 0.22 | 62 | 0.34 | −114 |
| | | 6000 | 0.58 | 85 | 1.1 | 21 | 0.27 | 63 | 0.43 | −135 |
| | 30 | 100 | 0.45 | −82 | 36.3 | 142 | 0.01 | 62 | 0.79 | −23 |
| | | 200 | 0.48 | −121 | 25.5 | 121 | 0.01 | 48 | 0.62 | −31 |
| | | 400 | 0.49 | −152 | 14.6 | 103 | 0.02 | 58 | 0.47 | −33 |
| | | 600 | 0.50 | −166 | 10.2 | 93 | 0.03 | 60 | 0.44 | −34 |
| | | 800 | 0.49 | −175 | 7.7 | 87 | 0.04 | 65 | 0.42 | −34 |
| | | 1000 | 0.48 | 177 | 6.1 | 81 | 0.05 | 76 | 0.43 | −37 |
| | | 1500 | 0.45 | 162 | 4.1 | 71 | 0.07 | 75 | 0.45 | −39 |
| | | 2000 | 0.45 | 145 | 3.0 | 62 | 0.09 | 78 | 0.44 | −46 |
| | | 2500 | 0.44 | 130 | 2.4 | 56 | 0.11 | 79 | 0.44 | −53 |
| | | 3000 | 0.50 | 113 | 1.9 | 50 | 0.13 | 79 | 0.45 | −58 |
| | | 3500 | 0.55 | 105 | 1.6 | 43 | 0.15 | 75 | 0.44 | −70 |
| | | 4000 | 0.61 | 92 | 1.5 | 39 | 0.19 | 73 | 0.45 | −76 |
| | | 5000 | 0.65 | 84 | 1.2 | 30 | 0.24 | 68 | 0.43 | −100 |
| | | 6000 | 0.61 | 82 | 1.0 | 19 | 0.28 | 64 | 0.48 | −135 |

Table 2. MRF9411LT1 Common Emitter S-Parameters (continued)

| V _{CE} (V _{dc}) | I _C (mA) | f (MHz) | NF _{min} (dB) | Γ _o (MAG, ANGLE) | Γ _N |
|---------------------------------------|------------------------|------------|---------------------------|--------------------------------|----------------|
| 6 | 5 | 1000 | 1.5 | 0.33 ∠ 77 | 0.28 |
| | | 1500 | 1.75 | 0.26 ∠ 141 | 0.3 |


Table 3. MRF947 Series Typical Noise Parameters

| V _{CE} (Volts) | I _C (mA) | f (MHz) | S ₁₁ | | S ₂₁ | | S ₁₂ | | S ₂₂ | |
|----------------------------|------------------------|------------|-----------------|------|-----------------|-----|-----------------|----|-----------------|-----|
| | | | Mag | ∠φ | Mag | ∠φ | Mag | ∠φ | Mag | ∠φ |
| 1.0 | 0.5 | 100 | 0.966 | −11 | 1.776 | 170 | 0.031 | 83 | 0.998 | −5 |
| | | 200 | 0.956 | −23 | 1.735 | 161 | 0.061 | 75 | 0.991 | −9 |
| | | 500 | 0.892 | −55 | 1.587 | 132 | 0.135 | 55 | 0.923 | −21 |
| | | 900 | 0.749 | −91 | 1.355 | 104 | 0.185 | 35 | 0.827 | −34 |
| | | 1000 | 0.720 | −100 | 1.300 | 98 | 0.190 | 32 | 0.808 | −36 |
| | | 1500 | 0.637 | −134 | 1.057 | 73 | 0.196 | 18 | 0.743 | −47 |
| | | 2000 | 0.587 | −164 | 0.883 | 53 | 0.176 | 12 | 0.708 | −58 |
| | | 3000 | 0.572 | 149 | 0.672 | 27 | 0.149 | 33 | 0.680 | −82 |
| | 1.0 | 100 | 0.941 | −14 | 3.391 | 168 | 0.031 | 81 | 0.991 | −6 |
| | | 200 | 0.921 | −28 | 3.285 | 158 | 0.060 | 73 | 0.974 | −12 |
| | | 500 | 0.806 | −65 | 2.844 | 128 | 0.123 | 51 | 0.852 | −27 |
| | | 900 | 0.638 | −104 | 2.196 | 101 | 0.158 | 35 | 0.717 | −39 |
| | | 1500 | 0.533 | −146 | 1.580 | 72 | 0.168 | 25 | 0.619 | −50 |
| | | 2000 | 0.495 | −174 | 1.281 | 55 | 0.164 | 25 | 0.581 | −60 |
| 2.0 | 0.5 | 3000 | 0.494 | 144 | 0.956 | 29 | 0.187 | 39 | 0.554 | −81 |
| | | 100 | 0.979 | −9 | 1.827 | 173 | 0.030 | 85 | 0.996 | −4 |
| | | 200 | 0.960 | −18 | 1.909 | 165 | 0.060 | 80 | 0.991 | −9 |
| | | 500 | 0.920 | −43 | 1.652 | 144 | 0.132 | 65 | 0.940 | −19 |
| | | 1000 | 0.749 | −77 | 1.451 | 116 | 0.196 | 47 | 0.842 | −32 |
| | | 1500 | 0.674 | −105 | 1.190 | 94 | 0.214 | 36 | 0.774 | −39 |
| | | 2000 | 0.548 | −128 | 1.077 | 79 | 0.189 | 33 | 0.692 | −43 |
| | 2.0 | 3000 | 0.480 | −178 | 0.808 | 60 | 0.153 | 55 | 0.625 | −52 |
| | | 100 | 0.907 | −16 | 6.640 | 167 | 0.029 | 81 | 0.977 | −9 |
| | | 200 | 0.846 | −32 | 6.419 | 156 | 0.054 | 73 | 0.944 | −17 |
| | | 500 | 0.711 | −68 | 4.874 | 128 | 0.104 | 57 | 0.770 | −32 |
| | | 1000 | 0.495 | −106 | 3.178 | 103 | 0.138 | 50 | 0.603 | −41 |
| | | 1500 | 0.405 | −131 | 2.358 | 86 | 0.157 | 52 | 0.542 | −45 |
| | | 2000 | 0.314 | −155 | 1.910 | 75 | 0.173 | 58 | 0.490 | −44 |
| | 5.0 | 3000 | 0.296 | 158 | 1.394 | 59 | 0.228 | 68 | 0.454 | −47 |
| | | 100 | 0.780 | −28 | 14.100 | 159 | 0.027 | 78 | 0.932 | −15 |
| | | 200 | 0.676 | −51 | 12.219 | 142 | 0.046 | 67 | 0.831 | −27 |
| | | 500 | 0.470 | −95 | 7.373 | 113 | 0.078 | 59 | 0.568 | −40 |
| | | 1000 | 0.327 | −132 | 4.148 | 92 | 0.114 | 62 | 0.436 | −43 |
| | | 1500 | 0.271 | −153 | 2.921 | 81 | 0.151 | 66 | 0.413 | −44 |
| | | 2000 | 0.218 | −177 | 2.295 | 72 | 0.188 | 69 | 0.394 | −41 |
| | | 3000 | 0.237 | 138 | 1.661 | 58 | 0.265 | 70 | 0.372 | −43 |

Table 4. MRF947 Series Common Emitter S-Parameters

| V _{CE} (Volts) | I _C (mA) | f (MHz) | S ₁₁ | | S ₂₁ | | S ₁₂ | | S ₂₂ | |
|----------------------------|------------------------|------------|-----------------|------|-----------------|-----|-----------------|----|-----------------|-----|
| | | | Mag | ∠φ | Mag | ∠φ | Mag | ∠φ | Mag | ∠φ |
| 2.0 | 10 | 100 | 0.608 | −43 | 21.812 | 149 | 0.022 | 72 | 0.859 | −23 |
| | | 200 | 0.488 | −73 | 16.618 | 129 | 0.038 | 65 | 0.689 | −35 |
| | | 500 | 0.330 | −119 | 8.427 | 103 | 0.065 | 66 | 0.438 | −41 |
| | | 1000 | 0.262 | −152 | 4.484 | 87 | 0.109 | 71 | 0.354 | −40 |
| | | 1500 | 0.227 | −169 | 3.114 | 77 | 0.155 | 73 | 0.358 | −42 |
| | | 2000 | 0.197 | 166 | 2.423 | 69 | 0.198 | 73 | 0.355 | −38 |
| | | 3000 | 0.233 | 128 | 1.755 | 57 | 0.281 | 71 | 0.338 | −40 |
| | 30 | 100 | 0.353 | −100 | 25.543 | 131 | 0.018 | 70 | 0.653 | −29 |
| | | 200 | 0.353 | −135 | 15.823 | 112 | 0.026 | 68 | 0.484 | −34 |
| | | 500 | 0.346 | −163 | 6.979 | 93 | 0.054 | 76 | 0.367 | −29 |
| | | 1000 | 0.337 | 177 | 3.637 | 80 | 0.103 | 79 | 0.351 | −30 |
| | | 1500 | 0.324 | 166 | 2.518 | 71 | 0.150 | 79 | 0.372 | −36 |
| | | 2000 | 0.319 | 148 | 1.975 | 63 | 0.197 | 78 | 0.378 | −35 |
| | | 3000 | 0.374 | 122 | 1.441 | 51 | 0.290 | 75 | 0.363 | −42 |
| 6.0 | 0.5 | 100 | 0.978 | −9 | 1.791 | 173 | 0.024 | 86 | 0.995 | −4 |
| | | 200 | 0.964 | −17 | 1.889 | 166 | 0.049 | 80 | 0.994 | −7 |
| | | 500 | 0.932 | −40 | 1.643 | 146 | 0.110 | 67 | 0.953 | −16 |
| | | 1000 | 0.765 | −73 | 1.473 | 121 | 0.165 | 50 | 0.869 | −28 |
| | | 1500 | 0.688 | −100 | 1.206 | 98 | 0.184 | 39 | 0.812 | −35 |
| | | 2000 | 0.554 | −123 | 1.099 | 84 | 0.162 | 38 | 0.735 | −38 |
| | | 3000 | 0.463 | −174 | 0.823 | 64 | 0.136 | 63 | 0.671 | −46 |
| | 2.0 | 100 | 0.918 | −15 | 6.614 | 168 | 0.023 | 84 | 0.983 | −7 |
| | | 200 | 0.862 | −29 | 6.456 | 157 | 0.045 | 75 | 0.956 | −14 |
| | | 500 | 0.729 | −62 | 5.010 | 131 | 0.089 | 60 | 0.809 | −27 |
| | | 1000 | 0.504 | −99 | 3.344 | 106 | 0.121 | 53 | 0.654 | −35 |
| | | 1500 | 0.397 | −123 | 2.485 | 90 | 0.137 | 55 | 0.599 | −38 |
| | | 2000 | 0.295 | −146 | 2.013 | 78 | 0.152 | 62 | 0.553 | −37 |
| | | 3000 | 0.257 | 162 | 1.452 | 62 | 0.202 | 73 | 0.523 | −40 |
| | 5.0 | 100 | 0.806 | −24 | 14.025 | 161 | 0.022 | 78 | 0.947 | −13 |
| | | 200 | 0.704 | −45 | 12.425 | 144 | 0.040 | 70 | 0.861 | −23 |
| | | 500 | 0.487 | −85 | 7.751 | 116 | 0.068 | 62 | 0.627 | −33 |
| | | 1000 | 0.316 | −120 | 4.399 | 95 | 0.101 | 65 | 0.505 | −35 |
| | | 1500 | 0.245 | −141 | 3.112 | 83 | 0.134 | 69 | 0.488 | −36 |
| | | 2000 | 0.177 | −166 | 2.447 | 74 | 0.167 | 72 | 0.473 | −33 |
| | | 3000 | 0.185 | 140 | 1.743 | 61 | 0.237 | 74 | 0.457 | −36 |
| | 10 | 100 | 0.657 | −37 | 22.098 | 151 | 0.019 | 75 | 0.888 | −18 |
| | | 200 | 0.526 | −64 | 17.304 | 132 | 0.033 | 68 | 0.741 | −29 |
| | | 500 | 0.328 | −105 | 9.028 | 106 | 0.056 | 67 | 0.509 | −33 |
| | | 1000 | 0.228 | −138 | 4.844 | 89 | 0.096 | 73 | 0.438 | −31 |
| | | 1500 | 0.184 | −156 | 3.359 | 80 | 0.138 | 75 | 0.440 | −34 |
| | | 2000 | 0.140 | 175 | 2.591 | 72 | 0.175 | 76 | 0.441 | −31 |
| | | 3000 | 0.172 | 126 | 1.852 | 60 | 0.249 | 75 | 0.430 | −33 |
| | 20 | 100 | 0.492 | −53 | 28.934 | 142 | 0.017 | 72 | 0.808 | −23 |
| | | 200 | 0.372 | −85 | 19.971 | 121 | 0.028 | 70 | 0.630 | −31 |
| | | 500 | 0.249 | −127 | 9.335 | 100 | 0.053 | 74 | 0.454 | −28 |
| | | 1000 | 0.201 | −156 | 4.878 | 86 | 0.094 | 78 | 0.418 | −27 |
| | | 1500 | 0.174 | −171 | 3.358 | 77 | 0.138 | 79 | 0.432 | −30 |
| | | 2000 | 0.149 | 161 | 2.580 | 70 | 0.177 | 78 | 0.444 | −28 |
| | | 3000 | 0.193 | 121 | 1.852 | 58 | 0.253 | 76 | 0.435 | −32 |


Table 4. MRF947 Series Common Emitter S-Parameters (continued)



$V_{CE} = 1.0 \text{ V}$
 $I_C = 0.5 \text{ mA}$
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 0.5 | 1.54 | $0.71 \angle 39^\circ$ | 38 | 0.28 |


Figure 15. MMBR941LT1, T3 Constant Gain and Noise Figure Contours (f = 1.0 GHz)



$V_{CE} = 1.0 \text{ V}$
 $I_C = 0.5 \text{ mA}$
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 1.0 | 1.95 | $0.55 \angle 76^\circ$ | 28 | 0.51 |


Figure 16. MMBR941LT1, T3 Constant Gain and Noise Figure Contours (f = 0.5 GHz)



$V_{CE} = 6.0$ V
 $I_C = 5.0$ mA
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 0.5 | 1.0 | $0.43 \angle 30^\circ$ | 18 | 0.58 |


Figure 17. MMBR941LT1, T3 Constant Gain and Noise Figure Contours
 ($f = 0.5$ GHz)



$V_{CE} = 6.0$ V
 $I_C = 5.0$ mA
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 1.0 | 1.5 | $0.22 \angle 64^\circ$ | 13 | 0.93 |


Figure 18. MMBR941LT1, T3 Constant Gain and Noise Figure Contours
 ($f = 1.0$ GHz)



$V_{CE} = 1.0 \text{ V}$
 $I_C = 0.5 \text{ mA}$
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 0.5 | 1.60 | $0.70 \angle 35^\circ$ | 40 | 0.22 |


Figure 19. MRF9411LT1 Constant Gain and Noise Figure Contours (f = 0.5 GHz)



$V_{CE} = 1.0 \text{ V}$
 $I_C = 0.5 \text{ mA}$
 — AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 1.0 | 1.95 | $0.55 \angle 69^\circ$ | 30 | 0.39 |

Figure 20. MRF9411LT1 Constant Gain and Noise Figure Contours (f = 1.0 GHz)




$V_{CE} = 6.0 \text{ V}$

$I_C = 5.0 \text{ mA}$

— AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 0.5 | 1.0 | $0.40 \angle 28^\circ$ | 17 | 0.29 |

Figure 21. MRF9411LT1 Constant Gain and Noise Figure Contours
(f = 0.5 GHz)



$V_{CE} = 6.0 \text{ V}$

$I_C = 5.0 \text{ mA}$

— AREA OF INSTABILITY

| f (GHz) | NF OPT (dB) | Γ_{MS} NF OPT | R_N | K |
|---------|-------------|------------------------|-------|------|
| 1.0 | 1.5 | $0.17 \angle 60^\circ$ | 13 | 0.53 |

Figure 22. MRF9411LT1 Constant Gain and Noise Figure Contours
(f = 1.0 GHz)

$V_{CE} = 6\text{ V}$
 $I_C = 5\text{ mA}$

| f (GHz) | NF OPT | Γ_O | R_N | K |
|------------|-----------|------------------------|-------|------|
| 1.0 | 1.5 dB | $0.33 \angle 77^\circ$ | 14 | 0.87 |




Figure 23. MRF947 Series Constant Gain and Noise Figure Contours

$V_{CE} = 6\text{ V}$
 $I_C = 5\text{ mA}$

| f (GHz) | NF OPT | Γ_O | R_N | K |
|------------|-----------|-------------------------|-------|------|
| 1.5 | 1.75 dB | $0.26 \angle 141^\circ$ | 15 | 0.96 |




Figure 24. MRF947 Series Constant Gain and Noise Figure Contours

$V_{CE} = 1\text{ V}$
 $I_C = 0.5\text{ mA}$

| f (GHz) | NF OPT | Γ_{MS} NF OPT | R_N | K |
|------------|-----------|-------------------------|-------|------|
| 1.0 | 1.95 dB | $0.59 \angle 72^\circ$ | 30 | 0.50 |





Figure 25. MRF947 Series Constant Gain and Noise Figure Contours

PACKAGE DIMENSIONS




- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: INCH.
 3. MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.

| DIM | INCHES | | MILLIMETERS | |
|-----|--------|--------|-------------|-------|
| | MIN | MAX | MIN | MAX |
| A | 0.1102 | 0.1197 | 2.80 | 3.04 |
| B | 0.0472 | 0.0551 | 1.20 | 1.40 |
| C | 0.0350 | 0.0440 | 0.89 | 1.11 |
| D | 0.0150 | 0.0200 | 0.37 | 0.50 |
| G | 0.0701 | 0.0807 | 1.78 | 2.04 |
| H | 0.0005 | 0.0040 | 0.013 | 0.100 |
| J | 0.0034 | 0.0070 | 0.085 | 0.177 |
| K | 0.0140 | 0.0285 | 0.35 | 0.69 |
| L | 0.0350 | 0.0401 | 0.89 | 1.02 |
| S | 0.0830 | 0.1039 | 2.10 | 2.64 |
| V | 0.0177 | 0.0236 | 0.45 | 0.60 |

- STYLE 6:
 PIN 1. BASE
 2. EMITTER
 3. COLLECTOR

CASE 318-08 ISSUE AF MMBR941LT1, T3, MMBR941BLT1




- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: INCH.

| DIM | INCHES | | MILLIMETERS | |
|-----|-----------|-------|-------------|------|
| | MIN | MAX | MIN | MAX |
| A | 0.071 | 0.087 | 1.80 | 2.20 |
| B | 0.045 | 0.053 | 1.15 | 1.35 |
| C | 0.035 | 0.049 | 0.90 | 1.25 |
| D | 0.012 | 0.016 | 0.30 | 0.40 |
| G | 0.047 | 0.055 | 1.20 | 1.40 |
| H | 0.000 | 0.004 | 0.00 | 0.10 |
| J | 0.004 | 0.010 | 0.10 | 0.25 |
| K | 0.017 REF | | 0.425 REF | |
| L | 0.026 BSC | | 0.650 BSC | |
| N | 0.028 REF | | 0.700 REF | |
| R | 0.031 | 0.039 | 0.80 | 1.00 |
| S | 0.079 | 0.087 | 2.00 | 2.20 |
| V | 0.012 | 0.016 | 0.30 | 0.40 |

- STYLE 3:
 PIN 1. BASE
 2. EMITTER
 3. COLLECTOR

CASE 419-02 ISSUE H MRF947AT1, MRF947BT1, MRF947T1, T3




- NOTES:
4. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 5. CONTROLLING DIMENSION: MILLIMETER.

| DIM | MILLIMETERS | | INCHES | |
|-----|-------------|------|--------|-------|
| | MIN | MAX | MIN | MAX |
| A | 2.80 | 3.04 | 0.110 | 0.120 |
| B | 1.20 | 1.39 | 0.047 | 0.055 |
| C | 0.84 | 1.14 | 0.033 | 0.045 |
| D | 0.39 | 0.50 | 0.015 | 0.020 |
| F | 0.79 | 0.93 | 0.031 | 0.037 |
| G | 1.78 | 2.03 | 0.070 | 0.080 |
| H | 0.013 | 0.10 | 0.0005 | 0.004 |
| J | 0.08 | 0.15 | 0.003 | 0.006 |
| K | 0.46 | 0.60 | 0.018 | 0.024 |
| L | 0.445 | 0.60 | 0.0175 | 0.024 |
| R | 0.72 | 0.83 | 0.028 | 0.033 |
| S | 2.11 | 2.48 | 0.083 | 0.098 |

STYLE 1:
 PIN 1: COLLECTOR
 2. EMITTER
 3. EMITTER
 4. BASE

**CASE 318A-05
 ISSUE R
 MRF9411LT1**

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:
USA / EUROPE: Motorola Literature Distribution;
 P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447

MFAX: RMFAX0@email.sps.mot.com - TOUCHTONE (602) 244-6609
INTERNET: <http://Design-NET.com>

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, Toshikatsu Otsuki,
 6F Seibu-Butsuryu-Center, 3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-3521-8315

HONG KONG: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



MOTOROLA



MMBR941/D

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.