

Is Now Part of



# **ON Semiconductor**®

To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor dates sheds, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor dates sheds and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use on similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor and its officers, employees, subsidiaries, affliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any lange of the applicatio customer's to unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the


September 2007



## BF247A N-Channel Amplifier

• This device is designed primarily for electronic switching applications such as low on resistance analog switching.

• Sourced from process 51.



## Absolute Maximum Ratings\* $T_a=25$ °C unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>DG</sub>	Drain-Gate Voltage	25	V
V <sub>GS</sub>	Gate-Source Voltage	-25	V
I <sub>GF</sub>	Forward Gate Current	10	mA
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range	-55 ~ +150	°C

\* This ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

#### NOTES:

1) These rating are based on a maximum junction temperature of 150 degrees C.

2) These are steady limits. The factory should be consulted on applications involving pulsed or low duty cycle operations.

## Thermal Characteristics T<sub>a</sub>=25°C unless otherwise noted

Symbol	Parameter	Max.	Units
PD	Total Device Dissipation	350	mW
_	Derate above 25°C	2.8	mW/°C
R <sub>0JC</sub>	Thermal Resistance, Junction to Case 125		°C/W
$R_{ ext{ heta}JA}$	Thermal Resistance, Junction to Ambient	357	°C/W

## Electrical Characteristics\* Ta=25°C unless otherwise noted

	ŭ				
Symbol	Parameter	Test Condition	Min.	Max.	Units

### **Off Characteristics**

••					
V <sub>(BR)GSS</sub>	Gate-Source Breakdown Voltage	$I_{G} = 1.0 \mu A, V_{DS} = 0$	-25		V
I <sub>GSS</sub>	Gate Reverse Current	$V_{GS} = 15V, V_{DS} = 0$		-5.0	nA
V <sub>GS(off)</sub>	Gate-Source Cut-off Voltage	$V_{DS} = 15V, I_{D} = 100nA$	-0.6	-14.5	V
V <sub>GS</sub>	Gate-Source Forward Voltage	$V_{DS} = 15V, I_{D} = 0.2mA$	-1.5	-4.0	V

#### **On Characteristics**

*I <sub>DSS</sub> Zero-Gate Voltage Drain Current * V <sub>DS</sub> = 15V, V <sub>GS</sub> = 0 30 80
--

### **Small Signal Characteristics**

	Forward Transformenductioned	$V_{PQ} = 15V$ , $V_{QQ} = 0V$	0	10
<b>g</b> fs	Forward Transferconductance	$v_{DS} = 15v, v_{GS} = 0v$	0	/12
* Pulse Test: Pulse Width ≤ 300μs, Duty Cycle = 2%				



SEMICONDUCTOR

#### TRADEMARKS

The following are registered and unregistered trademarks and service marks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx <sup>®</sup> Build it Now <sup>™</sup> CorePLUS <sup>™</sup> <i>CROSSVOLT</i> <sup>™</sup> CTL <sup>™</sup> Current Transfer Logic <sup>™</sup>	Green FPS™ Green FPS™ e-Series™ GTO™ <i>i-Lo</i> ™ IntelliMAX™ ISOPLANAR™	Power247 <sup>®</sup> POWEREDGE <sup>®</sup> Power-SPM <sup>™</sup> PowerTrench <sup>®</sup> Programmable Active Droop <sup>™</sup> QFET <sup>®</sup>	SuperSOT <sup>™</sup> -8 SyncFET <sup>™</sup> The Power Franchise <sup>®</sup> Pranchise TinyBoost <sup>™</sup>
EcoSPARK®	MegaBuck™ Micpocoupi ⊑p™	QS™	TinyBuck™ TinyLogio®
<b>F</b> Fairchild <sup>®</sup>	MICROCOUPLER™ MicroFET™	QT Optoelectronics™ Quiet Series™	TinyLogic <sup>®</sup> TINYOPTO™
Fairchild Semiconductor <sup>®</sup>	MicroPak™	RapidConfigure™	TinyPower™
FACT Quiet Series™	Motion-SPM™	SMART START™	TinyPWM™
FACT®	OPTOLOGIC®	SPM <sup>®</sup>	TinyWire™
FAST <sup>®</sup>	OPTOPLANAR®	STEALTH™	µSerDes™
FastvCore™	O.®	SuperFET™	UHC®
FPS™	PDP-SPM™	SuperSOT™-3	UniFET™
FRFET <sup>®</sup>	Power220 <sup>®</sup>	SuperSOT™-6	VCX™
Global Power Resource <sup>s™</sup>		· · · · · · · · · · · · · · · · · · ·	

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be pub- lished at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserve the right to make changes at any time without notice to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontin- ued by Fairchild semiconductor. The datasheet is printed for reference infor- mation only.

## PRODUCT STATUS DEFINITIONS

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Fairchild Semiconductor:BF247A\_QBF247ABF247A\_J35Z